

## Current transformer KBU 23 and KBU 58

|              | Current | VA / Class | Part. Nr. |
|--------------|---------|------------|-----------|
| <b>KBU23</b> | 100     | 1.25 / 1   | 940020    |
|              | 150     | 1.5 / 1    | 940021    |
|              | 200     | 1.5 / 1    | 940022    |
|              | 250     | 1.5 / 1    | 940023    |
|              | 300     | 1.5 / 1    | 940024    |
|              | 400     | 1.5 / 1    | 940025    |

|              | Current | VA / Class | Part. Nr. |
|--------------|---------|------------|-----------|
| <b>KBU58</b> | 400     | 5 VA / 1   | 940033    |
|              | 500     | 5 VA / 1   | 940036    |
|              | 600     | 5 VA / 1   | 940034    |
|              | 750     | 5 VA / 1   | 940037    |
|              | 800     | 7.5 VA / 1 | 940038    |
|              | 1'000   | 10 VA / 1  | 940039    |



| Current transformer | Width A (mm) | Height B (mm) | Depth C / C1 (mm) | Weight (kg) |
|---------------------|--------------|---------------|-------------------|-------------|
| <b>KBU23</b>        | 93           | 106           | 34 / 58           | 0.85        |
| <b>KBU58</b>        | 125          | 152           | 34 / 58           | 1.08        |

| Conductor rail | Width D (mm) | Length E (mm) |
|----------------|--------------|---------------|
| <b>KBU23</b>   | 20           | 30            |
| <b>KBU58</b>   | 50           | 80            |

